TMX S110 (TSF0915-04)

SAW BANDPASS FILTER - ISM


Preliminary Specification

All northernoon and include to represent the varieties of [259C, , 759C]				1		
All performances include temperature variations: [– 25°C; + 75°C]			Minimum	Typical ⁽¹⁾	Maximum	
Source impedance (single ended)		Ω		50 ⁽²⁾		
Load impedance (single ended)		Ω		50 ⁽²⁾		
Center frequency F _c		MHz		915		
Absolute attenuation						
300 kHz to 888 MHz		dB	30	34		
941 MHz to 2000 MHz		dB	30	37		
Maximum insertion loss in 902 MHz-928 MHz		dB		1.7	5.0	
Amplitude variation ⁽³⁾ in 902 MHz-928 MHz		dB		1.3	2.5	
VSWR in 902 MHz-928 MHz at 21°C				2.1: 1	2.5: 1	
Input power in 902 MHz-928 MHz		dBm			17	
Package type & size						
Length x Width		mm ²		3.8 x 3.8		
Height		mm		1.3	1.35	
Pin Out						
Input	2	Output	Output		5	
Case Ground	1, 3, 4, 6	To Be Ground	To Be Grounded		1, 3, 4, 6	

Notes:

- (1) Typical values are nominal performances at room temperature.
- (2) No external matching circuit is required.
- The amplitude variation is defined as the maximun level minimum level over the given bandwidth.

Input 50 Ω / Output 50 Ω configuration




TMX S110 (TSF0915-04)


SAW BANDPASS FILTER - ISM


Preliminary Specification


TYPICAL RESPONSE

Template is linked to specification over whole temperature range



















TMX S110 (TSF0915-04)

SAW BANDPASS FILTER - ISM

Preliminary Specification
Package

All dimensions are in mm

